

WIRELESS

Standards	Wi-Fi 5 IEEE 802.11ac/n/a 5 GHz IEEE 802.11n/b/g 2.4 GHz
WiFi Speeds	AC750 5 GHz: 433 Mbps (802.11ac) 2.4 GHz: 300 Mbps (802.11n)
WiFi Range	2 Bedroom Houses 4x Fixed Antennas Multiple antennas form a signal-boosting array to cover more directions and large areas
WiFi Capacity	Medium Dual-Band Allocate devices to different bands for optimal performance
Working Modes	Router Mode Access Point Mode Range Extender Mode

SEGURIDAD

Network Security	SPI Firewall Access Control IP & MAC Binding Application Layer Gateway
Guest Network	1x 5 GHz Guest Network 1x 2.4 GHz Guest Network
WiFi Encryption	WEP WPA WPA2 WPA/WPA2-Enterprise (802.1x)

HARDWARE

Processor	Single-Core CPU
Ethernet Ports	1x 10/100 Mbps WAN Port 4x 10/100 Mbps LAN Ports
Botones	WPS/Reset Button
Power	9 V – 0.6 A

SOFTWARE

Protocols	IPv4 IPv6
Parental Controls	URL Filtering Time Controls
WAN Types	Dynamic IP Static IP PPPoE PPTP L2TP
Quality of Service	QoS by Device
NAT Forwarding	Port Forwarding Port Triggering

SOFTWARE

	DMZ UPnP
IPTV	IGMP Proxy IGMP Snooping Bridge Tag VLAN
DHCP	Address Reservation DHCP Client List Server
DDNS	NO-IP DynDNS
Management	Tether App Webpage Check Web Emulator>

OTHER

System Requirements	Internet Explorer 11+, Firefox 12.0+, Chrome 20.0+, Safari 4.0+, or other JavaScript-enabled browser Cable or DSL Modem (if needed) Subscription with an internet service provider (for internet access)
Certifications	FCC, CE, RoHS
Environment	Operating Temperature: 0°C~40°C (32°F ~104°F) Storage Temperature: -40°C~60°C (-40°F ~140°F) Operating Humidity: 10%~90% non-condensing Storage Humidity: 5%~90% non-condensing

TEST DATA

WiFi Transmission Power	CE: <20dBm(2.4GHz) <23dBm(5GHz)
WiFi Reception Sensitivity	5GHz: 11a 54M: -76dBm; 11ac VHT20 MCS8: -71dBm; 11ac VHT40 MCS9: -66dBm; 11ac VHT80 MCS9: -62dBm 2.4GHz: 11g 54M: -76dBm; 11n HT20 MCS7: -73dBm; 11n HT40 MCS7: -71dBm

PHYSICAL

Dimensions (W×D×H)	4.5 × 4.2 × 1.0 in (115 × 106.7 × 24.3 mm)
Package Contents	Wi-Fi Router Archer C24 Power Adapter RJ45 Ethernet Cable Quick Installation Guide

For additional version information, please go to the [support page](#).